

# Cómo poner en marcha una PBX 3CX Gratuita en la Nube

El enlace de acceso para poder iniciar el proceso de puesta en marcha de la PBX de 3CX con hosting incluido es:

<https://www.3cx.com/phone-system/download-phone-system/>

Rellenar los campos y pulsar el botón: **Submit & Download**

## Your Business Phone System + Hosting. Free for 1 year.

Try 3CX's free Phone System Hosted on Google, OVH or on-premise

Get the free edition of 3CX's business VoIP phone system with one year free hosting on Google Cloud. 3CX's free business phone system **includes free web conferencing participants and unlimited extensions**. You can even bring your own SIP Trunk – no need to set up a new one. Use your free business phone system either on-premise on Windows or Linux or in the Cloud.

- ✓ **Hosted by 3CX** – a free phone system for one year
- ✓ **OR Self host** – on YOUR cloud account
- ✓ **On-premise:** on Windows or Linux
- ✓ **Zero admin** – automated admin tasks
- ✓ **Most secure** phone system on the market
- ✓ **WebRTC** based web conferencing
- ✓ **Mobility:** clients for Android, IOS, Windows and Mac

**Where do you start?** Fill in the form and you will receive an email with your licence key information and deployment instructions.

**Note:** Enter all your details correctly. You will need to verify your email address after which you will receive your free VoIP phone system licence key.

The one year free offer requires that you use the PBX. If less than 5 calls are made per month on the PBX, 3CX reserves the right to remove the PBX in order to save resources. This offer is only valid for new customers. If you have downloaded 3CX in the past and already have a licence key you are not eligible to use the one year free hosting.

The registration form is titled 'You are:' and has two radio buttons: 'Company' (selected) and 'Individual'. It contains the following fields: 'Name' (with a help icon), 'Surname', 'Company', a country dropdown set to 'Spain' with a '+34 Telephone' label, 'Area or ZIP Code (Select from the dropdown)', 'E-Mail', and 'Number of extensions' (with a dropdown arrow). At the bottom, there are two checkboxes: 'By checking this box I consent 3CX to contact me regarding this trial/product.' and 'I would like to be contacted by a 3CX Partner. I hereby give my consent (optional)'. A blue 'Submit & Download' button is at the bottom right.

Recibirá un correo con la información de la clave de licencia

You requested to download 3CX. Please click on the link below in order to verify your email address:

<https://customer.3cx.com/downloads/confirmemail.aspx?challenge=klkjfwzeoqsmm>

Once your email address is verified you will receive an email with your free license key details.

Pulsar sobre **el link...** y se mostrará la clave de licencia...

Pulsar sobre **Let 3CX Host for You.**

## Your email address has been confirmed.

This is your free 3CX license key for 1 year

**NLRQ-YIUK-2XQ3-VVOE**

Now all you need to do is to choose your deployment option:

Install on-premise

Deploy in Your Cloud

Let 3CX Host for You



### Verify your phone number

Get verification code on your phone and fill it in the form.

Phone

+34 630 04 32 00

Verification Code

Send Sms

Voice Call

Para verificar el contacto hay que introducir un número de teléfono móvil válido

Pulsar **Send SMS**

Introducir el código que habrá recibido por SMS

Verify your phone number

Get verification code on your phone and fill it in the form.

Phone

+34630043200

0

19

Voice Call

Next

Seleccionar **País // Hora // Lenguaje**

Select Time Zone, Country and Language

Select your country, time zone and Language. This is important for Call Reporting, Dialling rules, Phone configuration, invites, prompt set and notifications.

Select Country

Spain (+34)

Select the Time Zone

+1:00 Spain (Madrid, Palma)

Select Language

Standard English Prompts Set

Previous

Next

Introducir un nombre con el que queremos identificar el sistema 3CX (hostname). Junto con el dominio, éste será el FQDN asignado al sistema 3CX.

### Choose your preferred subdomain

This name will be used to create an FQDN and matching SSL certificate, and will be used for video conference invites and to configure your phones.

#### Hostname\*

#### Select a domain group

#### Select a domain

**IMPORTANT:** the FQDN/Subdomain you choose will be linked to your email & license key.

[Previous](#) [Next](#)

**IMPORTANTE:** el FQDN / Subdominio que elija estará vinculado a su correo electrónico y clave de licencia.

Seleccionar la longitud de dígitos para el plan de numeración de la PBX


#### Extension length

Choose the number of digits that extension numbers should have. The system reserves 30 extensions for system extensions. This cannot be changed later. Click "Next."

- 2 Digits (00-99)
- 3 Digits (000-999)
- 4 Digits (0000-9999)
- 5 Digits (00000-99999)

[Previous](#) [Next](#)

Elegir el servidor donde se alojará la PBX, preferiblemente Google Cloud Platform y en Europa

 **Google Cloud Platform**

Select Google Cloud region

Americas	<b>Europe</b>	Asia	Australia	South America
<input type="radio"/> Iowa	<input checked="" type="radio"/> <b>Belgium</b>	<input type="radio"/> Mumbai	<input type="radio"/> Sydney	<input type="radio"/> São Paulo
<input type="radio"/> Northern Virginia	<input checked="" type="radio"/> <b>Frankfurt</b>	<input type="radio"/> Taiwan		
<input type="radio"/> Oregon		<input type="radio"/> Tokyo		
<input type="radio"/> South Carolina		<input type="radio"/> Singapore		

[Previous](#) [Finish](#)

Al pulsar en **Finish**, comenzará el proceso de creación de la 3CX Cloud PBX.

Este proceso tarda unos 10 minutos aproximadamente en finalizar.

#### PBX creation

Copy and paste this information to a secure location! This dialog is displayed only ONE TIME! If you lose this information, you lose access to your installation.

**ARRIVAL TIME** 09 : 44

License key:	NLRQ-YIUK-2XQ3-VVOE
Emails to which info will be sent	jose_torrijos@hotmail.com
FQDN:	jatorrijos.3cx.es
Username:	admin
Password:	***** <a href="#">Show</a>
Preparing machine	Public IP: 35.1
Installing 3CX	

Una vez finalizado, será informado que ha finalizado la instalación.

Introduciendo el nombre de dominio en el navegador, podrá acceder al sistema 3CX para comenzar con el proceso de configuración de la PBX.



Una vez dentro de la administración de la PBX, tiene que realizar las pruebas de firewall.

A partir de este momento ya está disponible la PBX 3CX para funcionar. Configure los apartados necesarios para que el sistema esté operativo.